



Job Name: \_\_\_\_\_

Job Location: \_\_\_\_\_

Contractor: \_\_\_\_\_

Engineer: \_\_\_\_\_

Approval: \_\_\_\_\_

## Screw-In Water Heater Elements

### Design Features:

- 1" Screw in Plug
- Zinc Plated Copper Construction
- Includes Rubber Water Heater Gasket
- Individually Bagged
- .312" Diameter Tube
- Domestic



1940010



W-R#	Tube Length	Volts	Watts	Weight
1940002	7"	120V	1500W	.425 lbs.
1940004	7-1/4"	240V	2000W	.421 lbs.
1940005	11"	240V	3800W	.571 lbs.
1940006	10-1/8"	240V	3000W	.480 lbs.
1940007	12"	240V	3500W	.513 lbs.
1940008	12-7/8"	240V	4500W	.545 lbs.
1940010	8"	240V	5500W	.684 lbs.